


BA-1600-OSFP

1.6T DUAL-PORT BIT ANALYZER

- Achieve up to 3.2T testing capacity with two independent 1.6T OSFP ports. Test solution optimized for cable and transceiver validation.



KEY FEATURES

Test two 1.6T transceivers or an end-to-end high-speed interconnect using the dual OSFP ports

Full lifecycle validation for 1.6T, 800G and 400G across lab, fab and live environments

Superior hardware design: native OSFP interfaces, excellent signal quality, clean eye diagram and low error floor

Real-time FEC generation and analysis: testing of pre/post FEC BER, symbol error distribution and FEC margin

BLER: Block error ratio statistics and an efficient FLR estimation mechanism, addressing the time constraints of ultra-low BER measurements

PAM4 support for validating high-speed signaling performance

High-performance signal integrity and BER testing for validating compliance and performance in next-gen 1.6T transceivers and cables

User-friendly GUI streamlines workflows, and reduces learning curves

Powerful equalizer and channel simulator: powerful equalizer includes CTLE

I²C register read/write access enables the direct control and monitoring of device parameters for fast, low-level diagnostics and efficient debugging



“Save-and-load” functionality for all applicable parameters reduces valuable time and ensures test consistency

Automation simplifies complex test configurations and speeds up validation using a complete API suite

I²C Target 3-pin connector that allows for external control of the OSFP

POWERFUL AND SIMPLIFIED USER INTERFACE

The BA-1600 graphical user interface (GUI) provides simplified and real-time test results per channel. It requires an external Windows-based PC with Ethernet capability to run the GUI and API.



General Information		Module Specifics	
Module ID	OSFP	Current	Max
Vendor Name	OSFP	Module Temp	30.00°C
Part Number		Module Vdd	3.37V
Serial Number		Module Current	2.92A
Host Power SW	OSFP	Module Power	9.73W
Host Interface	IB		

Channel 1

BER: 6.08e-06 CDR

Errors: 8421258 Sync

Bits: 1,384 Gbits

Time: 6 s

Pre-FEC BER

Pre-FEC Error Bits

Total Bits

Time/Second

Currently active App Code: 7

Target App Code: Auto

Application Selector	Host Interface ID	Media Interface ID	Host Lane Count	Media Lane Count	Host Lane Assignment	Media Lane Assignment
1	IB XDR(A0h)	800GBASE-DR4(77h)	4	4	00010001b	00010001b
2	IB XDR(A0h)	400GBASE-DR2(75h)	2	2	01010101b	01010101b
3	IB XDR(A0h)	200GBASE-DR1(73h)	1	1	11111111b	11111111b
4	200GAUI-1(80h)	200GBASE-DR1(73h)	1	1	11111111b	11111111b
5	400GAUI-2(91h)	400GBASE-DR2(75h)	2	2	01010101b	01010101b
6	800GAUI-4(82h)	800GBASE-DR4(77h)	4	4	00010001b	00010001b
7	1.6TAUI-8(83h)	1.6TBASE-DR8(7Fh)	8	8	00000001b	00000001b
8	End of list(FFh)	Undefined(00h)	0	0	00000000b	00000000b

Channel 5

PreFEC BER: 9010 9.08e-11

Cor-CW: 8733 CDR

BLER: 0 0.00e+0

FLR-64: 0.00e+00

PostFEC BER: 0.00e+00

Est-PostFEC BER: 0.00e+00

Margin: 13

CodeWs: 18,240,161,364

Time: 937 s

Pre-FEC Error Bits

Pre-FEC BER

Correctable Codewords

Block Error Ratio

Sum of blocks with ≥ 16 symbol errors

Frame Loss Ratio-Oct


Post-FEC BER

Estimated Post-FEC BER

FEC Margin

Total Codewords

Time/Second



FEC channel distribution and BLER mask testing

Board Type: OSFP, **QSFPDD**

Power Supply: 6.553500 V

HW Signals: LPWn, RSTn, PRSh, **Int**

I2C register: Address 12, Value 12, R, **W**

MCB control

Clock Ratio: Rate/2, Rate/4, **Rate/8**, Rate/16, Rate/32

Enable output Clock: Channel 3 **Enable** Disable

Clock output Channel: Channel 1, Channel 2, Channel 3, Channel 4, Channel 5, Channel 6, Channel 7, Channel 8

Buttons: Cancel, **Apply**

Reference clock

WITH PAM4 CODING, A SIMPLE BER TEST IS NOT ENOUGH

Channel 1

Pre-FEC-BER: 187164, 2.83e-11

Cor-CW: 186819, CDR

CER: 0, 0.00e+0

FLR-64: 0.00e+0

Est-CER: 0.00e+00

Est-FLR: 0.00e+0

Margin: 13

CodeWws: 1,217,412,998,765

Time: 62561 s

FEC symbol error margin


EXFO FEC 10G.25GbE PAM4

BER Configuration: Run, Clear, Force Relock

Number of Symbols	Ch 1	Ch 2	Ch 3	Ch 4	Ch 5	Ch 6	Ch 7	Ch 8
1	0	111	8	32	1	0	0	0
2	0	18	0	0	0	0	0	0
3	0	0	0	0	0	0	0	0
4	0	0	0	0	0	0	0	0
5	0	0	0	0	0	0	0	0
6	0	0	0	0	0	0	0	0
7	0	0	0	0	0	0	0	0
8	0	0	0	0	0	0	0	0
9	0	0	0	0	0	0	0	0
10	0	0	0	0	0	0	0	0
11	0	0	0	0	0	0	0	0
12	0	0	0	0	0	0	0	0
13	0	0	0	0	0	0	0	0
14	0	0	0	0	0	0	0	0
15	0	0	0	0	0	0	0	0

BER Monitor: Channel 1, TX Invert, Pre Cursor2, RX Invert, Amplitude, Post 1-7, Lower Eye, Upper Eye

FEC symbol error distribution plot



Channel histogram


14-tap mode

TX Invert, RX Invert, Pre Cursor2, Pre Cursor1, Amplitude, Post 1-7, Floating Position, Lower Eye, Upper Eye

14-tap mode

DESIGNED FOR HIGH-SPEED AND MULTISERVICE

- 1 Power button
- 2 Display (4.5 inch)
- 3 Air inlet
- 4 Foot rest
- 5 Screen switch button
- 6 Grounding jack
- 7 I2C Target 3-pin connector
- 8 OSFP cage



SPECIFICATIONS

SPECIFICATIONS	
Number of ports	2
Data rate per lane (GBd)	106.25, 53.125 and 26.5625
Data rate adjustment (ppm)	±250
PAM4 coding	Gray code
Pattern supported by PPG and ED	PPG: PRBS 7Q/9Q/10Q/11Q/13Q/15Q/20Q/23Q/31Q/49Q/58Q/SSPRQ/SQUARE_WAVE ED: PRBS 7Q/9Q/10Q/11Q/13Q/15Q/20Q/23Q/31Q/49Q/58Q ^a
PG maximum amplitude (mV _{ppd})	900
Jitter RMS (mUI)	≤23
EOJ03 (mUI)	≤25
JH4u (mUI)	≤135
ED maximum level (mV _{ppd})	1200
ED damage level (mV _{ppd})	1300
TX multi tap pre-emphasis support	10 fix taps + 4 floating taps ^b
Connector type	OSFP IHS

GENERAL SPECIFICATIONS	
Size (H × W × D)	105 mm × 465 mm × 350 mm (4.1 in × 18.3 in × 13.8 in)
Weight	≤ 5 kg (11 lb)
Temperature	Operating: 0 °C to 40 °C (32 °F to 104 °F) Storage: -40 °C to 70 °C (-40 °F to 158 °F)
Relative humidity	≤95% non-condensing
Power	100 Vac to 240 Vac (47 Hz to 63 Hz) 200W typical / 300W max

ACCESSORIE	
GP-3277	19" relay rack mounting bracket + screws/HW

a. Only 13Q, 20Q, 23Q, 31Q, 49Q, 58Q patterns are supported in RX at 106.25 GBaud.

b. Max 14 UI away from fix taps.

EXFO headquarters T +1 418 683-0211 **Toll-free** +1 800 663-3936 (USA and Canada)

EXFO serves over 2000 customers in more than 100 countries. To find your local office contact details, please go to www.EXFO.com/contact.

For the most recent patent marking information, please visit www.EXFO.com/patent. EXFO is certified ISO 9001 and attests to the quality of these products. EXFO has made every effort to ensure that the information contained in this specification sheet is accurate. However, we accept no responsibility for any errors or omissions, and we reserve the right to modify design, characteristics and products at any time without obligation. Units of measurement in this document conform to SI standards and practices. In addition, all of EXFO's manufactured products are compliant with the European Union's WEEE directive. For more information, please visit www.EXFO.com/recycle. **Contact EXFO for prices and availability or to obtain the phone number of your local EXFO distributor.**

For the most recent version of this spec sheet, please go to www.EXFO.com/specs.

In case of discrepancy, the web version takes precedence over any printed literature.